

导播通话系统

**导播通话系统****ITC-100**

|              |  |
|--------------|--|
| Tally 接口     | 2 x 15 Pin DSub Sockets for Tally A and B  |
| 耳机麦克风接口      | 3.5 mm Stereo Jack Socket for Headphone / Microphone combination<br>Headset Impedance 8-600 Ohms 100 mW (min)  |
| 耳机接口         | ¼" (6.3mm) Stereo Headphone Socket<br>Headset Impedance 8-600 Ohms 100 mW (min)  |
| 灯光接口(DC 12V) | 3 PIN XLR Connector<br>PIN 2: 12V<br>PIN 3: GND<br>Light Power Consumption: 12 V / 100 mA (MAX.)   |
| 麦克风接口        | 3 PIN XLR / ¼" (6.3mm) Jack Microphone Socket<br>Switchable Condenser / Dynamic Input<br>Microphone Level -67 dB   |
| 频率响应         | 550-3.6 kHz, <+/- 3dB  |
| 总谐波失真(THD)   | < 3%   |
| 信号杂讯比(S/N)   | > 50dB   |
| 内建麦克风        | 70mm x 30mm 32 Ohm 3 Watts   |
| 操作范围         | Up to 200 meters between base station and slave  |
| 操作温度         | 0~40 °C  |
| 尺寸           | 482 x 127 x 46 mm  |
| 重量           | 1.9 kg   |
| 电源           | DC 12V, 8W   |
| 包装明细         | 1 x ITC-100 Base Unit<br>4 x ITC-100SL Belt Pack<br>4 x ITC-100SL Carry Case<br>4 x Cable 5pin XLR to XLR<br>4 x 3.5mm Jack to 3.5mm Jack Cable<br>4 x Headset with microphone<br>4 x Tally LED Indicator<br>1 x XLR Gooseneck Microphone<br>1 x XLR Gooseneck Light<br>1 x 12V 1A Power Supply Unit |